



POWERING YOUR *life.*

82001i-E-DF [-EU]

WARRANTY: 3 Years

2000

STARTING WATTS
Propane: 1800

1600

RUNNING WATTS
Propane: 1440

RUN TIME 11 hrs

NOISE LEVEL 53dBA



EZ START DIAL
Confusion free **ENGINE START-UP**



DIGITAL LED DISPLAY
Output, run time, fuel life and level



CLEAN ELECTRICITY
Power **SENSITIVE ELECTRONICS**



COLD START
Easy starts in **COLD WEATHER**




PARALLEL READY
Link 2 units for **DOUBLE POWER**
PARALINK

Receptacles



12V DC
Automotive




240V or 220V
UK or EU model

Specifications

START TYPE	Recoil
VOLTAGE (V)	240 (UK) or 220 (EU)
ENGINE SIZE (cc)	80
FUEL TYPE	Petrol or Propane
PETROL CAPACITY (L)	4.1
OIL TYPE	10W-30
OIL CAPACITY (L)	0.38
LOW OIL SHUT-OFF	Yes
CERTIFICATION	CE

*Specifications, descriptions and illustrations are subject to change without notice.



Innovative, versatile power is yours with the Champion 2000-watt Dual Fuel inverter generator. Rely on the 80cc engine and enjoy a quiet 53 dBA for up to 11 hours of run time. Double your output with the optional ParaLINK Parallel Kit (not included).

Inside the box

- GENERATOR
- OPERATORS MANUAL
- OIL FUNNEL
- 12V USB ADAPTER
- LPG HOSE

What you will Need

- PETROL
- ENGINE OIL (10W-30)

RETAIL PACKAGE (gross)
Weight: 25.5 kg
Size: 56 x 37 x 52cm



PRODUCT (net)
Weight: 21.5 kg
Size: 52 x 33 x 43cm

CHAMPION POWER EQUIPMENT EU
Unit 17-18, Bradley Hall Trading Estate
Bradley Lane, Standish, Wigan, WN6 0XQ, UK
www.championpowerequipment.eu